

## Master List of Formulas and Symbology Descriptions

**Disclaimer:** Here are some common formulas; however this is not an exhaustive list and you may not need all of them.

### Video Camera Image Size

$$IS = 2 * D * \tan\left(\frac{A}{2}\right)$$

Where *IS* is the image size  
*D* is the distance from the lens to the subject  
*A* is the lens angle of view

### Projector Lumens Output

$$Brightness = \frac{\left(\frac{L * C * A}{Sg}\right)}{Dr}$$

Where *L* is ambient light at screen location\*  
*C* is the desired contrast ratio  
 7:1 – Passive Viewing – Television  
 15:1 – Basic Decision Making Presentations  
 50:1 – Analytical Decision Making – Art work, Medical  
 80:1 – Full Motion Video – Home Theater  
*A* is the area of screen \*\*  
*Sg* is the gain of the screen. Assume a screen gain of 1 unless otherwise noted.  
*Dr* is the projector derating value. Assume a derating value of 0.75 unless otherwise noted.

\* Light units are in either lux or footcandles  
 \*\* area in square meters or square feet

### Loudspeaker Coverage Pattern (Ceiling Mounted)

$$D = 2 * (H - h) * \tan\left(\frac{C_z}{2}\right)$$

Where *D* is diameter of coverage circle at ear height  
*H* is overall ceiling height  
*h* is height of the listener's ears (48 inches)  
*C<sub>z</sub>* is off-axis coverage angle of polar pattern

### Loudspeaker Spacing (Ceiling Mounted)

$$D = 2 * r \quad \text{(Edge-to-edge)}$$

$$D = r * \sqrt{2} \quad \text{(Minimum overlap)}$$

$$D = r \quad \text{(Center-to-center)}$$

Where *D* is the distance between loudspeakers  
*r* is the radius of loudspeaker coverage circle

### Wattage at the Loudspeaker

$$EPR = 10^{\left(\frac{L_p + H - L_s + 20 \log\left(\frac{D_2}{D_r}\right)}{10}\right)} * W_{ref}$$

Where *EPR* is electrical power required at loudspeaker  
*L<sub>p</sub>* is SPL required at distance *D<sub>2</sub>*  
*H* is required headroom  
*L<sub>s</sub>* is loudspeaker sensitivity at 3.28 feet (1 m)  
*D<sub>2</sub>* is distance from loudspeaker to listener  
*D<sub>r</sub>* is distance reference value  
*W<sub>ref</sub>* is the wattage reference value. Assume a wattage reference value of 1 unless otherwise noted.

**Parallel Loudspeaker Impedance**

$$Z_T = \frac{1}{\frac{1}{Z_1} + \frac{1}{Z_2} + \frac{1}{Z_3} \dots \frac{1}{Z_N}}$$


$$Z_T = \frac{Z_1}{N}$$

Where  $Z_T$  is the total impedance of the loudspeaker system  
 $Z_1$  is the measured impedance of a loudspeaker  
 $N$  is the quantity of loudspeakers in the circuit

**Ohm's Law Related**

$$I = \frac{P}{V}$$

Where  $I$  is current  
 $V$  is circuit voltage  
 $P$  is power \*



\* Look up amplifier power in owner's manual before adding to the other AV devices.

**Needed Acoustic Gain**

$$NAG = 20 \log \left( \frac{D_0}{EAD} \right)$$

Where  $NAG$  is Needed Acoustic Gain  
 $D_0$  is distance from source to listener  
 $EAD$  is Equivalent Acoustic Distance

**Potential Acoustic Gain**

$$PAG = 20 \log \left( \frac{D_0 * D_1}{D_2 * D_s} \right)$$

Where  $PAG$  is Potential Acoustic Gain  
 $D_0$  is distance from source to listener  
 $D_1$  is distance from loudspeaker to mic  
 $D_2$  is distance from loudspeaker to listener  
 $D_s$  is distance from source to microphone

**Audio System Stability (PAG NAG Complete Formula)**

$$20 \log_{10} \left( \frac{D_0}{EAD} \right) < 20 \log_{10} \left( \frac{D_0 D_1}{D_2 D_s} \right) - 10 \log_{10}(NOM) - FSM$$

Where  $NOM$  = Number of Open Microphones  
 $FSM$  = Feedback Stability Margin  
 $EAD$  = Equivalent Acoustic Distance  
 $D_0$  = the distance between the talker and the farthest listener  
 $D_1$  = the distance between the closest loudspeaker to the microphone and the microphone  
 $D_2$  = the distance between the loudspeaker closest to the farthest listener and the farthest listener  
 $D_s$  = the distance between the sound source (talker) and the microphone

**Power Amplifier Wattage (Constant Voltage)**

$$W_t = W * N * 1.5$$

Where  $W_t$  is required wattage  
 $W$  is watt tap used at individual loudspeaker  
 $N$  is total number of loudspeakers  
 1.5 is 50 percent amplifier headroom

**Power Amplifier Heat Load**

$$Total BTU = W * 3.4 * (1 - E_D)$$

Where  $Total BTU$  is the total British Thermal Units released  
 $W$  is the wattage of the amplifier  
 $E_D$  is the efficiency of the device

<p><b>Heat Load</b></p> $Total\ BTU = W_E * 3.4$ <p>Where <i>Total BTU</i> is the total British Thermal Units released  <i>W<sub>E</sub></i> is the total watts of equipment in the room</p>	<p><b>Jam Ratio</b></p> $JAM = \frac{ID}{\left(\frac{OD_1 + OD_2 + OD_3}{3}\right)}$ <p>Where ID is the inner diameter of the conduit  OD is the outer diameter of each conductor</p>
<p><b>Conduit Capacity</b></p> <p>Where <i>ID</i> is the inner diameter of the conduit  <i>OD</i> is outer diameter of each conductor</p>	$ID > \sqrt{\frac{OD^2}{0.53}} \quad \text{One Cable}$ $ID > \sqrt{\frac{OD^2 + OD^2}{0.31}} \quad \text{Two Cables}$ $ID > \sqrt{\frac{OD^2 + OD^2 + OD^2 \dots}{0.40}} \quad \text{3+ Cables}$
<p><b>Computer Video Signal Bandwidth</b></p> $HF = \frac{H_{pix} * V_{pix} * f_v}{2} * 3$ <p>Where <i>HF</i> is the highest frequency in Hertz  <i>H<sub>pix</sub></i> is the total number of horizontal pixels  <i>V<sub>pix</sub></i> is the total number of vertical pixels  <i>f<sub>v</sub></i> is the refresh rate</p>	<p><b>Minimum Video System Bandwidth</b></p> $SF = HF * 2$ <p>Where <i>SF</i> is the system frequency in Hertz  <i>HF</i> is the highest frequency in Hertz of the computer signal</p>
<p><b>Digital Video Data Rate</b></p> $R = H_{pix} * V_{pix} * C * 1.25 * FPS * 3$ <p>Where <i>R</i> is the data rate in bits per second  <i>H<sub>pix</sub></i> is the total number of horizontal pixels  <i>V<sub>pix</sub></i> is the total number of vertical pixels  <i>C</i> is the color depth (bit depth) in bits  <i>FPS</i> is the number of frames per second</p>	<p><b>Minimum Task Lighting</b></p> $Light_{Min} = \frac{\left(\frac{L_P}{A}\right)}{3}$ <p>Where <i>Light<sub>Min</sub></i> is the minimum task lighting in Lux  <i>L<sub>P</sub></i> is projector lumens  <i>A</i> is the area of the screen in meters squared</p> <p>*Assume unity gain unless otherwise directed.</p>